



Specifications	
Part Number	CSTCE10M0G55Z-R0
Manufacturer	Murata Electronics
Description	CER RES 10.0000MHZ 33PF SMD
Category	Crystals, Oscillators, Resonators > Resonators
Part Status	3000 pcs Stock
Series	CERALOCK® CSTCE
Frequency	10MHz
Operating Temperature	-40°C ~ 125°C
Mounting Type	Surface Mount
Size / Dimension	0.126" L x 0.051" W (3.20mm x 1.30mm)
Type	Ceramic
Impedance	-
Features	Built in Capacitor
Height	0.031" (0.79mm)
Capacitance	33pF
Package / Case	3-SMD, Non-Standard
Frequency Stability	±0.2%
Frequency Tolerance	±0.5%
Packaging	Tape & Reel (TR)

In:

CSTCE10M0G52Z-R0
Murata Electronics
CER RESONATOR



More

- | | | | | |
|----------------------|-----------------------|----------------------|----------------------|----------------------|
| ➡ CSTCC6.00MG-TC | ➡ CSTCC6M00G53-R0 | ➡ CSTCC6M32G33A80-R0 | ➡ CSTCC6M40G23A01-R0 | ➡ CSTCC7M92G53A-R0 |
| ⚡ CSTCC8.00MG-TC | ⚡ CSTCC8.00MG16953-TC | ⚡ CSTCC8.00MGA-TC | ➡ CSTCC8.19MGA-TC | ➡ CSTCC8M00G26A-R0 |
| ⚡ CSTCC8M00G53-R0 | ⚡ CSTCC8M00G53A-R0 | ⚡ CSTCC8M00G53A72-R0 | ➡ CSTCC8M19G53A-R0 | ➡ CSTCC8M38G53-R0 |
| ⚡ CSTCC9.83MG0H6-TC | ⚡ CSTCC9M00G53-R0 | ⚡ CSTCC9M83G56-R0 | ⚡ CSTCE10M0G52-R0 | ➡ CSTCE10M0G52-R0 |
| ➡ CSTCE10M0G52A | ➡ CSTCE10M0G52A-R0 | ⚡ CSTCE10M0G52W-R0 | ⚡ CSTCE10M0G52Z-R0 | ➡ CSTCE10M0G55-R0 |
| ➡ CSTCE11M0G52001-R0 | ➡ CSTCE11M6G52-R0 | ⚡ CSTCE12M0G15027-R0 | ⚡ CSTCE12M0G52-R0 | ⚡ CSTCE12M0G55-R0 |
| ⚡ CSTCE12M0G55A-R0 | ⚡ CSTCE12M0GH5L05-R0 | ➡ CSTCE12M0GH5L11-R0 | ➡ CSTCE12M0GH5L16-R0 | ➡ CSTCE12M2G52-R0 |
| ⚡ CSTCE12M2G55-R0 | ⚡ CSTCE12M5G52-R0 | ➡ CSTCE12M5G55-R0 | ➡ CSTCE12MOG15050-R0 | ➡ CSTCE13M5V53-R0 |
| ⚡ CSTCE14M0V51-R0 | ⚡ CSTCE14M7V53-R0 | ⚡ CSTCE15M5V53-R0 | ⚡ CSTCE16M0V13C73-R0 | ➡ CSTCE16M0V13C99-R0 |
| ➡ CSTCE16M0V13L02-R0 | ⚡ CSTCE16M0V51-R0 | ⚡ CSTCE16M0V51-R0 | ⚡ CSTCE16M0V53-R0 | ➡ CSTCE16M5V53W-R0 |